

По вопросам продаж и поддержки обращайтесь:

Архангельск (8182)63-90-72	Краснодар (861)203-40-90	Санкт-Петербург (812)309-46-40
Астана (7172)727-132	Красноярск (391)204-63-61	Саратов (845)249-38-78
Астрахань (8512)99-46-04	Курск (4712)77-13-04	Севастополь (8692)22-31-93
Барнаул (3852)73-04-60	Липецк (4742)52-20-81	Симферополь (3652)67-13-56
Белгород (4722)40-23-64	Магнитогорск (3519)55-03-13	Смоленск (4812)29-41-54
Брянск (4832)59-03-52	Москва (495)268-04-70	Сочи (862)225-72-31
Владивосток (423)249-28-31	Мурманск (8152)59-64-93	Ставрополь (8652)20-65-13
Волгоград (844)278-03-48	Набережные Челны (8552)20-53-41	Сургут (3462)77-98-35
Вологда (8172)26-41-59	Нижний Новгород (831)429-08-12	Тверь (4822)63-31-35
Воронеж (473)204-51-73	Новокузнецк (3843)20-46-81	Томск (3822)98-41-53
Екатеринбург (343)384-55-89	Новосибирск (383)227-86-73	Тула (4872)74-02-29
Иваново (4932)77-34-06	Омск (3812)21-46-40	Тюмень (3452)66-21-18
Ижевск (3412)26-03-58	Орел (4862)44-53-42	Ульяновск (8422)24-23-59
Казань (843)206-01-48	Оренбург (3532)37-68-04	Уфа (347)229-48-12
Калининград (4012)72-03-81	Пенза (8412)22-31-16	Хабаровск (4212)92-98-04
Калуга (4842)92-23-67	Пермь (342)205-81-47	Челябинск (351)202-03-61
Кемерово (3842)65-04-62	Ростов-на-Дону (863)308-18-15	Череповец (8202)49-02-64
Киров (8332)68-02-04	Рязань (4912)46-61-64	Ярославль (4852)69-52-93
	Самара (846)206-03-16	

Единый адрес: psx@nt-rt.ru Веб-сайт: www.pixsys.nt-rt.ru

Преобразователи температуры PIXSYS. Техническое описание

The transmitters for DIN/B head convert a signal acquired by temperature probes PT100, PT1000 or Ni100 (with 2-, 3- and 4-wire connections) or Thermocouples into a 4..20 mA signal (2-wire technology), current-loop. These converters ensure high accuracy on the reading scale with 16-bit conversion and possibility to rescale the output 4..20mA basing on input range.



Available also the version with galvanical isolation (cod. 2000.35.015).

Quick and simple programming

The programming procedure uses the RFid (NFC) function with a dedicated programmer that allows you to perform all settings and any calibrations quickly without the need power and connect up the converter. An App for mobile and Android devices equipped with an NFC antenna makes it possible to program, modify and see data directly in the field or on the move.

2.8K Word non volatile (circular buffer) memory are dedicated to a data-logging function with a sampling time that can be set by the user.

The RF-Programmer software (available to download from the reserved access area of the website) allows you to download, view on the PC and print the temperature-time curve.

Ordering codes

2000.35.010

RTD (PT100/NI100/PT1000) > 4...20mA Loop Powered

2000.35.015

RTD (PT100/Ni100) + TC (K-S-R-J-T-N-B-E) > 4...20mA Loop Powered - isolated version

2000.35.012

Programmer RF/RFID > USB

Main features

Box

23 mm, Ø 45 mm

Power supply

Loop Power (2 wires connection) operating range 6-32 Vdc

Connection

Screw pins

Fixing

On DIN/B head

Operating conditions

Temperature -40+85 °C, humidity 30..90 uR% (non condensing)

Material

Nylon (PA66)

Weight

Approx. 30 g

Sealing

IP 20

According to

CE, EN 61000-6-4, EN 61000-6-2, UL 61010-1

Programming

Wireless with RFid technology (NFC)

Technical data

Output resolution

1 µA

Over-range output

f.s. + 5°C

Under-range output

f.s. - 5°C

Error output

Selectable between 21,5mA or 3,8mA

Current output protection

Approx. 30 mA

Rejection

50-60 Hz

Max. transmission error

Greater between 0,1% f.s. or 0,2°C

Sampling/response time

300msec / 600 msec

Cable resistance

Max 20Ω

Temperature coefficient

< 100 ppm

По вопросам продаж и поддержки обращайтесь:

Архангельск (8182)63-90-72	Краснодар (861)203-40-90	Санкт-Петербург (812)309-46-40
Астана (7172)727-132	Красноярск (391)204-63-61	Саратов (845)249-38-78
Астрахань (8512)99-46-04	Курск (4712)77-13-04	Севастополь (8692)22-31-93
Барнаул (3852)73-04-60	Липецк (4742)52-20-81	Симферополь (3652)67-13-56
Белгород (4722)40-23-64	Магнитогорск (3519)55-03-13	Смоленск (4812)29-41-54
Брянск (4832)59-03-52	Москва (495)268-04-70	Сочи (862)225-72-31
Владивосток (423)249-28-31	Мурманск (8152)59-64-93	Ставрополь (8652)20-65-13
Волгоград (844)278-03-48	Набережные Челны (8552)20-53-41	Сургут (3462)77-98-35
Вологда (8172)26-41-59	Нижний Новгород (831)429-08-12	Тверь (4822)63-31-35
Воронеж (473)204-51-73	Новокузнецк (3843)20-46-81	Томск (3822)98-41-53
Екатеринбург (343)384-55-89	Новосибирск (383)227-86-73	Тула (4872)74-02-29
Иваново (4932)77-34-06	Омск (3812)21-46-40	Тюмень (3452)66-21-18
Ижевск (3412)26-03-58	Орел (4862)44-53-42	Ульяновск (8422)24-23-59
Казань (843)206-01-48	Оренбург (3532)37-68-04	Уфа (347)229-48-12
Калининград (4012)72-03-81	Пенза (8412)22-31-16	Хабаровск (4212)92-98-04
Калуга (4842)92-23-67	Пермь (342)205-81-47	Челябинск (351)202-03-61
Кемерово (3842)65-04-62	Ростов-на-Дону (863)308-18-15	Череповец (8202)49-02-64
Киров (8332)68-02-04	Рязань (4912)46-61-64	Ярославль (4852)69-52-93
	Самара (846)206-03-16	

Единый адрес: psx@nt-rt.ru **Веб-сайт:** www.pixsys.nt-rt.ru